

## SC-6000 Lite



Cadru tratat pentru a preveni ruginirea



Alternator produs si patentat de Senci



Filtru de aer patentat

Generator Senci	SC-6000 Lite
Plaja tensiune	230-235 V
Plaja frecventa	50-55 Hz
Putere max.	5.5 kW
Putere in regim continuu	5.0 kW
Regulator de tensiune	AVR
Tip motor Senci	AP188F
Putere motor Senci	13cp/389cmc
Rotatii motor	3000 rpm
Demaraj	la sfoara
Racire	Aer
Carburant	Benzina
Capacitate rezervor	25 l
Autonomie (100% putere)	8.5 ore
Autonomie (50% putere)	13.5 ore
Zgomot la 7 metri	97 dB
Dimensiuni (L x l x h mm)	625 x 480 x 500
Greutate utilaj	75 kg



Panou comanda

### Echipare standard:

Alternator Senci de calitate superioara  
 Alerta nivel ulei scazut cu oprire automata a motorului  
 Senzor de suprasarcina cu auto-oprire  
 Filtru de aer nou, mai mic cu un design deosebit ce reduce consumul de ulei si creste puterea generatorului  
 Silentios si prietenos cu mediul  
 Regulator de tensiune AVR  
 Portabil, compact, cadru rezistent  
 Pentru uz casnic dar si comercial  
 Panou de control rezistent la ploaie si praf  
 1 priza 230V 16A, 1 priza 230V 32A  
 Multimetru digital cu afisare: tensiune, frecventa, contor ore



[www.italiastar.ro](http://www.italiastar.ro)



Italia Star Com Due S.R.L.  
 Autostrada Bucuresti - Pitesti km. 13.2  
 Loc. Chiajna - Ilfov  
 Tel: 021.433.03.27  
 Fax: 021.433.03.26  
[info@italiastar.ro](mailto:info@italiastar.ro) [www.italiastar.ro](http://www.italiastar.ro)

